

# Surface Mounted Series

Remote Emergency Lighting Fixtures



## LT1/LT2/LT3 Series

- PAR36, surface-mounted, large remote fixtures
- Single, double or triple head
- Positive aim swivel
- Available in factory white (standard) and black



## VQ1/VQ2/VQW Series

- Cubic, vandal-resistant surface-mounted fixture
- Single, double or twin cube with center body
- Available in factory white (standard) and black with frosted polycarbonate cube



Project/Location:

Date:

C

A

PM

I

LS

Contractor:


Prepared by:

# Surface Mounted Series

## LT Series

### Dimensions

LT1:	4.5" (11.4 cm) L x 7.25" (18.4 cm) H x 3.5" (8.9 cm) D Canopy: 5.0" (12.7 cm) Diameter
LT2:	4.5" (11.4 cm) L x 7.25" (18.4 cm) H x 11.75" (29.9 cm) D Canopy: 5" (12.7 cm) Diameter
LT3:	14.0" (35.6 cm) L x 7.25" (18.4 cm) H x 14.0" (35.6 cm) D Canopy: 9.5" (24.1 cm) Diameter



### Ordering Information

Series	# of Heads	Voltage/Wattage/Lamp Type	Colour	Options
LT= tungsten, par 36	1= single	-6/9= 6V - 9 watts, tungsten, wedge base	Blank= factory white	TC= teflon coated lens
LQ= halogen, par 36	2= double	-6/ __ = 6V - 18 or 25 watts, tungsten, D.C.B.	BK= black	
LS= tungsten sealed beam	3= triple	-12/ __ = 12V - 9 or 18 watts, tungsten, wedge base		
LH= halogen quartz sealed beam		-12/25= 12V - 25 watts, tungsten, D.C.B.		
		-24/ __ = 24V - 9 or 18 watts, tungsten, wedge base		
		-24/25= 24V - 25 watts, tungsten, D.C.B.		
		-6 __ = 6V - 8, 12, or 20 watts, halogen, quartz bi-pin		
		-12/ __ = 12V - 8, 12, 20 or 55 watts, halogen, quartz bi-pin		
		-24/ __ = 24V - 20 or 70 watts, halogen, quartz bi-pin		
		-6/ __ = 6V - 9, 12, 18 or 25 watts, tungsten, sealed beam		
		-12/ __ = 12V - 12, 18 or 25 watts, tungsten, sealed beam		
		-6/ __ = 6V - 8, 12 or 20 watts, halogen, quartz sealed beam		
		-12/ __ = 12V - 8, 12 or 37 watts halogen, quartz sealed beam		
		-32/ __ = 32V - 18 or 25 watts, tungsten, D.C.B.		
		-120/ __ = 120V - 10, 15, 30 or 50 watts, tungsten, D.C.B.		
		*NOTE: "__"= insert wattage required		

EXAMPLE: LQ1-12/12

## VQ Series

### Dimensions

VQ1:	4.4" (11.2 cm) L x 4.8" (12.2 cm) H x 4.4" (11.2 cm) D
VQ2:	9.4" (23.9 cm) L x 5.75" (14.6 cm) H x 4.4" (11.2 cm) D
VQW:	14.8" (37.6 cm) L x 4.88" (12.4 cm) H x 4.88" (12.4 cm) D



### Ordering Information

Series	Lamp Type	# of Heads	Lamp Style/Wattage	Options	Colour
V= Series	T= tungsten	1= single cube	-6/9= 6V - 9 watts, wedge base	Blank= no options	Blank= factory white
	Q= halogen	2= twin cubes	-12/9= 12V - 9 watts, wedge base	TP= tamper proof screws	BK= black
		W= double cube	-12/18= 12V - 18 watts, wedge base		
			-24/9= 24V - 9 watts, wedge base		
			-6/8= 6V - 8 watts, quartz bi-pin		
			-6/12= 6V - 12 watts, quartz bi-pin		
			-12/8= 12V - 8 watts, quartz bi-pin		
			-12/12= 12V - 12 watts, quartz bi-pin		
			-24/20= 24V - 20 watts, quartz bi-pin		
			MI= 6V - 6 watts, MR16		
			MJ= 6V - 10 watts, MR16		
			MK= 12V - 12 watts, MR16		
			MA= 12V - 20 watts, MR16		
			MB= 12V - 35 watts, MR16		
			MC= 12V - 50 watts, MR16		
			MD= 24V - 20 watts, MR16		
			ME= 24V - 35 watts, MR16		
			MF= 24V - 50 watts, MR16		

EXAMPLE: VQ1-6/8-TP

**Thomas & Betts**